

FusionPBX

Configuration Sip Trunk

1. Dans Accounts > Gateways: rajouter un compte

Gateway

Defines a connections to a SIP Provider or another SIP server.

Gateway	<input type="text" value="OVH"/> <small>Enter the gateway name here.</small>
Username	<input type="text" value="0032"/> <small>Enter the username here.</small>
Password	<input type="password" value="....."/> <small>Enter the password here.</small>
From User	<input type="text"/> <small>Enter the from-user here.</small>
From Domain	<input type="text"/> <small>Enter the from-domain here.</small>
Proxy	<input type="text" value="sip5.ovh.be"/> <small>Enter the hostname or IP address of the proxy. host[:port]</small>
Realm	<input type="text" value="sip5.ovh.be"/> <small>Enter the realm here.</small>
Expire Seconds	<input type="text" value="1800"/> <small>Enter the expire-seconds here.</small>
Register	<input checked="" type="checkbox" value="True"/> <small>Choose whether to register.</small>
Retry Seconds	<input type="text" value="30"/> <small>Enter the retry-seconds here.</small>
<input type="button" value="⚙️ ADVANCED"/>	
Context	<input type="text" value="public"/> <small>Enter the context here.</small>
Profile	<input type="text" value="external"/> <small>Enter the profile here.</small>

2. Dans Advanced > Access control: rajouter l'IP Wan du serveur SIP Trunk dans la règle Providers

Access Control

Access control list can allow or deny ranges of IP addresses.

Name	<input type="text" value="providers"/>	Enter the name.												
Default	<input type="button" value="deny"/>	Select the default type.												
Nodes	<table border="1"><thead><tr><th>Type</th><th>CIDR</th><th>Description</th><th>Action</th></tr></thead><tbody><tr><td><input type="button" value="allow"/></td><td><input type="text" value="91.121.129.133/32"/></td><td><input type="text" value="OVH"/></td><td><input type="checkbox"/></td></tr><tr><td><input type="button" value=""/></td><td><input type="text"/></td><td><input type="text"/></td><td><input type="checkbox"/></td></tr></tbody></table>	Type	CIDR	Description	Action	<input type="button" value="allow"/>	<input type="text" value="91.121.129.133/32"/>	<input type="text" value="OVH"/>	<input type="checkbox"/>	<input type="button" value=""/>	<input type="text"/>	<input type="text"/>	<input type="checkbox"/>	Enter the description.
Type	CIDR	Description	Action											
<input type="button" value="allow"/>	<input type="text" value="91.121.129.133/32"/>	<input type="text" value="OVH"/>	<input type="checkbox"/>											
<input type="button" value=""/>	<input type="text"/>	<input type="text"/>	<input type="checkbox"/>											
Description	<input type="text"/>	Enter the description												

3. Dans Status > Sip Status: Relancer les ACL

4. Dans Dialplan > Destination: Ajouter une règle pour le numéro entrant

Destination

Inbound destinations are the DID/DDI, DNIS or Alias for inbound calls.

Type	<input type="button" value="Inbound"/>	Select the type.
Country Code	<input type="text"/>	Enter the country code.
Destination	<input type="text" value="003:"/>	Enter the destination.
Caller ID Name	<input type="text"/>	Enter the caller ID name.
Caller ID Number	<input type="text"/>	Enter the caller ID number.
Context	<input type="text" value="public"/>	Enter the context.
Conditions	<input type="text"/> <input type="text"/>	If the condition matches perform the action.
Actions	<input type="button" value="3000 AppelEntrant"/> <input type="button" value=""/>	Add additional actions.
User	<input type="text"/>	Assign this destination to a user.

From: <https://wiki.makeitsimple.be/> - makeITsimple wiki

Permanent link: <https://wiki.makeitsimple.be/doku.php?id=linux:fusionpbx&rev=1712821862>

Last update: 2024/04/11 07:51

